

○ PCT-610 / PCT-620: Integrated Mixer Amplifiers

Fully integrated mixer amplifiers incorporating mic/line inputs with in-built Tuner and CD music sources. With a whole host of functions, the PCT Series is ideal for high specification PA systems, church and AV applications using the RS232 control option for remote access and control.

Features:

- 120W/240W Output
- 6 Inputs (Mic/Line XLR)
- Individual phantom power per input
- Priority mic 1, mic 2
- Telephone input (screw terminals)
- External mute (screw terminals)
- External chime (screw terminals)
- RM-05A Mic input (D-type)
- RS232 Control (D-type)
- 230v AC/24v DC powered
- Aux in/out (¼" jack)
- In-built CD and tuner music sources
- IR Remote control (optional)
- 3U high, 19" rack mounting

Specifications:

| Model: | PCT-610: | PCT-620: |
|-----------------------------|--|--|
| Output Power | 120W RMS @ 100v | 240W RMS @ 100v |
| Inputs | 6 x Mic/Line Selectable (3 pin XLR) | 6 x Mic/Line Selectable (3 pin XLR) |
| Priority | Mic 1, Mic 2, Chime, EM, Telephone Input | Mic 1, Mic 2, Chime, EM, Telephone Input |
| Phantom Power | Individually switched per input | Individually switched per input |
| Input Sensitivity/Impedance | Inputs 1~6 ~ -60dB~-16dB 1mv / 10k Ω | Inputs 1~6 ~ -60dB~-16dB 1mv / 10k Ω |
| Frequency Response | 80Hz ~ 20KHz | 80Hz ~ 20KHz |
| Link In | 100mv / 10kΩ | 100mv / 10kΩ |
| Amp In | 1v / 47kΩ | 1v / 47kΩ |
| Pre Amp Out | 1v / 600Ω | 1v / 600Ω |
| Power Requirement | 230v AC 50Hz / 24v DC | 230v AC 50Hz / 24v DC |
| Dimensions | 482(W) x 132(H) x 380(D)mm | 482(W) x 132(H) x 380(D)mm |
| Weight | 8.5kg | 9.5kg |

